

# BLUETOOTH AUDIO RECEIVER QUICK INSTALL GUIDE

MODEL 161091

Thank you for your purchase of the MANHATTAN® Bluetooth Audio Receiver, Model 161091.

Quickly installed with a 3.5 mm stereo plug, it pairs with PCs, MP3 players, mobile phones and other Bluetooth-enabled media sources to convert most speakers into a wireless entertainment system.

(Instructions on back of this sheet.)

- Built-in rechargeable battery provides up to 6.5 hours of listening almost anywhere
- Compact, integrated design requires no external antenna
- Lifetime Warranty



## SPECIFICATIONS

### Standards/Certifications

- CE, QRB
- Bluetooth V 2.1

### General

- Streaming format: SBC 48 kHz
- Frequency range: 20 Hz–22 kHz
- Power: built-in rechargeable lithium-polymer battery with overcharge protection, (approx. 3 hrs. recharge time; 6.5 hrs. operating time)

- Power adapter/recharger:
  - Input, 100–240 V AC, 50–60 Hz, 0.2 A
  - Output, 5.0 V / 0.2 A
  - Cable, 97 cm (38 in.)
- Connections: 3.5 mm stereo (line out); DC 5 V (power in)
- Dimensions: 9 x 8 x 3 cm (3.5 x 3.15 x 1.2 in.)
- Weight: 122 g (4.3 oz.)

### Bluetooth

- Class 2
- A2DP protocol support
- Effective range: up to 20 m (65.6 ft.)
- 748 kbps data rate

### Package Contents

- Bluetooth Audio Receiver
- Power adapter/recharger
- Quick install guide



MANHATTAN® offers a complete line of PC Components, Peripherals, Cables and Accessories. Ask your local computer dealer for more information or visit us online at

**[www.manhattan-products.com](http://www.manhattan-products.com)**

Copyright © MANHATTAN

All products mentioned are trademarks or registered trademarks of their respective owners.

MH-161091-miniQIG-1109-02



## SETUP & OPERATING INSTRUCTIONS



Prior to the initial use of the Bluetooth Audio Receiver, its built-in battery needs to be fully charged. The first charge can take up to 4 hours, while subsequent recharging may take less than 3 hours.

### Charging the Battery

- Plug the included power adapter/recharger into an AC outlet, then connect it to the In DC 5V jack on the receiver (above-left image).
- The middle LED (between the On/Off buttons) will light green to indicate the battery is charging, then turn off to indicate a full charge (above-right image).

### Bluetooth Pairing and Operation

1. Connect your speakers to the 3.5 mm stereo Line Out jack on the Bluetooth Audio Receiver.
2. Power on the receiver by pressing the On button, and keep it pressed (for approximately 4 seconds) until the red and blue LEDs (between the On/Off buttons) flash back and forth. The receiver is now in its pairing mode. **NOTE:** Whenever the pairing between devices is not maintained for a full minute or so, the pairing function will stop and need to be re-established.
3. Turn on your Bluetooth-enabled device (mobile phone, PC, notebook, etc.) and activate its Bluetooth pairing per the device's BT instructions. **NOTE:** To play music using a Bluetooth-enabled mobile phone, the phone needs to support A2DP and AVRCP profiles.
4. When your Bluetooth-enabled device locates the receiver and displays it (as "BT Speakers") in its Devices list, select the receiver for pairing.
5. When the display of your Bluetooth-enabled device prompts you to enter a PIN code, enter 0000 (zeroes). This should complete the pairing process — indicated by the flashing blue LED — and place the receiver in standby mode, automatically connecting to your Bluetooth-enabled device.
6. At this point, the receiver is ready to relay sound to your speakers. **NOTE:** To avoid unwanted syncing, turn the receiver off when it's not in use.